

## stabo multifon home guard

433 MHz wireless alarm system

*comfortable home protection*

... comfortable home protection

via Apps for iOS/Android

### Scope of Supply:

base station with GSM module\* and integrated backup Li-Ion battery (3.7 V / 1200 mAh)  
power supply unit (12 V / 1 A)  
wireless door/window contact (batt. included)  
wireless PIR sensor (batt. included)  
2 wireless remote controls (batt. included)  
mounting material  
User manual (DE/EN)  
\*SIM card not included

Art.-Nr. 51125

### Technical data

Radio frequency 433 MHz  
Radio range Up to 100 m (free field)

### Base station

GSM frequency 850/ 900/ 1800/ 1900 MHz  
GSM transm. power 2 watts  
Power supply Power supply unit 12 V/DC, 1 A  
Emergency power supply Li-Ion batt. pack 3.7 V/1.2 Ah

Operating period of emergency power supply approx. 8 hours

Stand-by current ≤ 35 mA  
Alarm current ≤ 120 mA  
Charging current ≤ 140 mA  
Working temperature - 10°C ~ 40°C  
Humidity 5% to 95%  
Dimensions (WxHxD) 180 x 130 x 30 mm  
Weight 240 g

### Radio door/window contact

Stand-by current ≤ 30 µA  
Alarm current ≤ 40 mA  
Power supply 1.5 V LR6  
Operating period ≤ 12 months  
Dimensions (WxHxD) 34 x 70 x 19 mm  
Weight 44 g (incl. battery pack)

### Radio motion detector

Stand-by current ≤ 50 µA  
Alarm current ≤ 10 mA  
Detection angle ≤ 110°  
Width of detection ≤ 12 m  
Power supply 9 V block battery  
Operating period ≤ 12 months  
Dimensions (WxHxD) 60 x 105 x 42 mm  
Weight 90 g (incl. battery pack)

### Radio remote control

Power supply 12 V (type 27 A)

### optional accessoires:

wireless door/window contact (batt. incl.)	51126
wireless PIR sensor (batt. incl.)	51127
wireless remote control (batt. incl.)	51228

### Art.-Nr.

... with notification by phone in the event of an alarm



Via a radio link, the motion detector and door/window contact report interferences to the base station. In this case, an acoustic alarm (internal siren) is triggered and/or the integrated GSM module is used to make a phone call or to transmit a SMS to previously defined phone numbers.

All settings and queries can be done with your smartphone/tablet PC (free app for iOS/Android).

The basic set includes a PIR motion sensor (e.g. for the entrance area) and a door/window contact (e.g. for the basement exit), additional sensors (up to 15) extend the secured area.

■ **integrated GSM module\***  
(850/900/1800/1900 MHz)

■ **all functions controllable via APP**  
(iOS / ANDROID)

■ **16 zones for wireless,**  
**4 zones for wired sensors**

■ **range of sensors up to 100 m**  
(under optimum conditions)

■ **5 phone numbers programmable** (for notifications in the event of an alarm (call or SMS))

■ **sabotage protection**

■ **integrated temperature control**  
(min./max. value)

■ **Integrated siren/ connection for external siren**

■ **Arm/alarm delay adjustable** (max. 59 sec.)

■ **5 relay outputs** (On/Off)

■ **Backup battery**

### Wireless PIR sensor:

● On/off switch

● Area of coverage 110°, range up to 12 m

### Wireless door/window contact:

● Sabotage protection

● Emergency call triggering